



### Charcoal Filters

x2 Round 6  
1 filter each side of the motor\*

### Fuse Type

3 amp

### Duct Size (Round)

125mm Minimum  
(150mm Standard)

### Metal Grease Filters

LA-60-Curva x1 250x270  
LA-90-Curva x2 250x223

\*You must measure your mesh grill size. Older models will have different sizes to current models\*

### Warranty

5 Years (2 Years Parts & Labour + 3 Years Parts Only)

### EEI Rating

A+

### Remote Control

N/A

### Lighting

1x LED Strip 6w 4000 Kelvin

### Motor

800m<sup>3</sup>/hr Brushless Motor

### Switch Type

Touch Sensitive

### Extraction Rate (Unrestricted)

#### Speed 1

220m<sup>3</sup>/hr

#### Speed 2

360m<sup>3</sup>/hr

#### Speed 3

500m<sup>3</sup>/hr

#### Boost Function

720m<sup>3</sup>/hr

### Noise Levels DB/A

42 DB

52DB

62 DB

69 DB

### Timer Function

Up To 90 Mins

Up To 90 Mins

Up To 90 Mins

### Box Dimensions (CM) & Weight

LA-60-CURVA	70x59x66	21.5Kg
LA-90-CURVA	99x59x66	29.8Kg